

## **NSP-1404B**

## **Dual-Switch Dual-Light™ Flashlight- Non-Rechargeable**

**MARKET APPLICATIONS** 

Law enforcement, fire & rescue, industrial, security, hardware/tool, automotive, hunting/recreation.

DESCRIPTION

This non-rechargeable dual-switch Dual-Light™ flashlight has two body switches offering the user a choice of flashlight, floodlight or dual-light operation. Its compact oval design makes it convenient to use and carry. The water resistant housings are made from engineered polymer and have a soft touch finish. The light a white flashlight and a green floodlight and comes with a removable pocket/belt clip. Power comes from 2 included AAA batteries.

**CASE MATERIAL** Engineered Polymer - Black

**DIMENSIONS** Length: 5.3 inches (135 mm) • Handle diameter: 1.1 x 0.8 inches (28 x 20 mm)

**WEIGHT** Weight: 2.2 oz. (62 g) with batteries installed.

LIGHT SOURCE
Unbreakable polycarbonate with scratch resistant coating.
Cree® LED. Impervious to shock with a 50,000 hour lifetime.
Flashlight - 60 lumens, Green Floodlight - 10 lumens

**ON/OFF** Top Body Switch - Flashlight, Bottom Body Switch - Floodlight

**RUN-TIME** Flashlight - 3 hours, Floodlight -5.5 hours **BATTERY** 2 AAA Premium Batteries (included)

• CREE® LED technology – 50,000+ hours LED

· Flashlight/Green Floodlight

- · Focused flashlight beam for distance illumination
- · Unfocused wide-beam floodlight for close-up illumination
- · Green floodlight for night vision preservation
- · Engineered polymer housing with Soft-touch finish
- · Dual body switches
- · Non-slip grip
- · Water resistant
- Impact & chemical resistant polymer housing
- · Powered by 2 AAA premium batteries (included)

WARRANTY

\*Limited 1 Year Warranty - Product is warranted to be free from defects in workmanship and materials to the original purchaser for one (1) year from the date of purchase, and includes the LEDs, housing, lenses, electronics, switches, rechargeable batteries and chargers. Disposable non-rechargeable batteries are excluded from this warranty. Normal wear and failures which are caused by accidents, misuse, abuse, faulty installation and lightning damage are also excluded.

## **APPROVALS**





